

KANLUX IQ-LEDDIM A60 5,5W

Dimmer	1 IQ-LEDDIM lamp		2 IQ-LEDDIM lamps		4 IQ-LEDDIM lamps	
Manufacturer – model	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]

AURORA AU-DSP400X 240V 60-400W	0%	100%	0%	100%	0%	100%
RS16/400 GLI 230V 400W	9%	100%	10%	100%	10%	100%
RS16/315 GLE 230V 300W	8%	100%	6%	100%	5%	100%
JQP401W 230V 10-400W 50HZ	5%	99%	4%	99%	4%	99%
32ELEDM	10%	99%	10%	99%	9%	99%
Dignet MEDM	1%	99%	1%	99%	1%	99%
067083A 16W05 31 CXM14	6%	95%	6%	95%	6%	95%
Dignet LED XPERT DGRT	5%	99%	5%	99%	6%	99%
Licht-Management 225NV DE AC 230/240V 20-500W 50HZ	10%	100%	10%	100%	10%	100%
225 NVDE	9%	100%	9%	100%	10%	100%
P250 34373 TQP251W 216-253V 40-250W	1%	100%	1%	100%	1%	100%
MK K1534RPWHI 230V 40-250W	4%	100%	3%	100%	3%	100%
MARBO HDR-250 200-240V 60-250W	1%	100%	1%	100%	1%	100%
Wickes W195127W 230-240V 330W	1%	100%	1%	100%	1%	100%
MARBO HDR-400 200-240V 60-400W	1%	100%	1%	100%	1%	100%
Wickes W711324W 200-240V 60-400W	1%	100%	1%	100%	1%	100%
P400 87222 TQP401W 216-253V 60-400W	1%	100%	1%	100%	1%	100%
Govena PRO-250-LT-LED	9%	95%	9%	95%	9%	95%

* Kanlux SA is not liable for the results of design changes introduced by the manufacturers of the above-mentioned dimmers that can affect the compatibility with Kanlux IQ-LEDDIM light sources

KANLUX IQ-LEDDIM A60 12,5W

Dimmer	1 IQ-LEDDIM lamp		2 IQ-LEDDIM lamps		4 IQ-LEDDIM lamps	
	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]

KAOYI KDT-200A 220-240V 5-200W	3%	99%	3%	99%	3%	99%
CLIPSAL 32E450LM 220-240V 20-450W	10%	99%	10%	99%	10%	99%
CLIPSAL 32E450TM 220-240V 50Hz 10-450W	8%	99%	8%	99%	8%	99%
CLIPSAL 32E450UMD 220-240V 50Hz 450W	10%	99%	10%	99%	10%	99%
marisio Dimmer Resistivo 110V 20-150W(220V 40-300W)	4%	98%	4%	98%	4%	98%
CLIPSAL 32E450LM 220-240V 50Hz 20-450W	6%	98%	6%	98%	6%	98%
bticino L-N-NT4411N 110/127 3-200W(220/230V 3-400W)	5%	95%	5%	95%	5%	95%
P250 34373 TQP251W 216-253V 40-250W	3%	98%	5%	98%	5%	98%
MK K1534RPWHI 230V 40-250W	8%	98%	9%	98%	9%	98%
C0143 250W	0%	98%	0%	98%	0%	98%
P400 87222 TQP401W 216-253V 60-400W	2%	98%	2%	98%	2%	98%
Wickes W195127W 230-240V 330W	0%	98%	0%	98%	0%	98%
MARBO HDR-400 200-240V 60-400W	0%	98%	0%	98%	0%	98%
Wickes W711324W 200-240V 60-400W	0%	99%	0%	99%	0%	99%
MEG5133-0000 230V 50HZ 40-600W/VA	0%	98%	0%	98%	0%	98%
MEG6136-0000 230V 50HZ 20-315W/VA	6%	98%	6%	98%	6%	98%
Phasenabschnitt-Dimmer 8078 230V 50HZ 20/275W	10%	99%	9%	99%	9%	99%
Busch-Dimmer 2247 U 230V 50HZ 500W/VA	5%	98%	5%	96%	8%	98%
KOPP 230V 50HZ 40-400W arktis-weiB 809702013	0%	96%	0%	96%	0%	96%
GIRA 2262 230/240V 20-500W 50HZ	5%	98%	5%	98%	5%	98%
Busch-Dimmer 6519U 230V 50HZ 550W/VA	10%	96%	10%	96%	10%	96%
RS16/315 GLE 230V 300W	1%	98%	1%	98%	1%	98%
ABB 2251 UCGL-92-507 230V 50Hz 400W	1%	98%	1%	98%	1%	98%
DANLERS 230V 60-400W	0%	98%	0%	98%	0%	98%
Dimmer Switch 2	5%	98%	5%	98%	5%	98%
ZGRID500	0%	99%	0%	99%	0%	99%
Elektronischer Dimmer 40-400VA 230V 10% 50HZ	0%	98%	0%	98%	0%	98%
L2501G2W PKA014 UK	0%	98%	0%	98%	0%	98%
CCTEL12011	5%	98%	5%	98%	5%	98%
Busch-Dimmer Phasenabschnitt	10%	98%	10%	98%	10%	98%
ELECTRONIC Dimmer SKU#290998 LD-KDT-200A 220-240V 50HZ 5-200W T1.6AH 250VAC	9%	95%	9%	95%	9%	95%
32ELEDM	4%	99%	4%	99%	4%	99%
Dignet MEDM	0%	99%	0%	99%	0%	99%
Dignet LED XPRT DGRT	0%	99%	0%	99%	0%	99%
CLIPSAL LED dimmer 32ELEDM	4%	98%	4%	98%	4%	98%
32E450TM	8%	99%	8%	99%	8%	99%
067083A 16W05 31 CXM14	4%	94%	5%	94%	5%	94%
CLIPSAL 32E450LM 220-240V 20-450W	8%	93%	8%	93%	8%	93%
Govena PRO-250-LT-LED	7%	99%	5%	99%	5%	99%

KANLUX IQ-LEDDIM A60 15W

Dimmer	1 IQ-LEDDIM lamp		2 IQ-LEDDIM lamps		4 IQ-LEDDIM lamps	
Manufacturer – model	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]	minimum level [%]	maximum level [%]

CLIPSAL 32E450LM 220-240V 20-450W	2%	98%	6%	98%	7%	98%
HPM legrand Cat 400T 230-240V 50Hz 10-400W	5%	99%	5%	99%	5%	100%
Clipsal Lead 32E450LM	3%	100%	4%	100%	5%	100%
ELECTRONIC Dimmer SKU#290998 LD-KDT-200A 220-240V 50HZ 5-200W T1.6AH 250VAC	2%	99%	2%	99%	3%	99%
AURORA AU-DSP400X 240V 60-400W	1%	99%	1%	99%	1%	100%
RS16/315 GLE 230V 300W	2%	99%	1%	99%	1%	100%
JQP401W 230V 10-400W 50HZ	1%	92%	1%	93%	1%	94%
REV Ritter GmbH Frankenstr 1-4 D-63776	1%	99%	2%	99%	2%	99%
CLIPSAL 32E450TM	9%	100%	9%	100%	9%	100%
32ELEDM	4%	100%	4%	100%	4%	100%
Dignet MEDM	0%	100%	0%	100%	0%	100%
KAOYI KDT-200A	4%	99%	3%	99%	2%	99%
067083A 16W05 31 CXM14	3%	93%	3%	93%	3%	92%
CLIPSAL 32E450UMD 220-240V 450W	8%	99%	8%	100%	8%	100%
MEG5133-0000 230V 50HZ 40-600W/VA	1%	99%	1%	100%	1%	100%
6523UJGL-214	8%	99%	8%	99%	8%	100%
CCTFL12011	6%	99%	5%	99%	4%	100%
EBS81P-XD 14W16	7%	100%	8%	100%	8%	100%
MK K1534RPWHI 230V 40-250W	3%	93%	4%	96%	5%	97%
C0143 250W	1%	98%	1%	99%	1%	100%
MARBO HDR-250 200-240V 60-250W	1%	99%	1%	99%	1%	100%
Wickes W195127W 230-240V 330W	1%	99%	1%	99%	1%	99%
V-PRO 94816 JQP401W 230V 10-400W	1%	92%	1%	93%	1%	94%
MARBO HDR-400 200-240V 60-400W	1%	99%	1%	99%	1%	100%
Wickes W711324W 200-240V 60-400W	1%	99%	1%	99%	1%	100%
P400 87222 TQP401W 216-253V 60-400W	1%	99%	1%	99%	1%	99%
Govena PRO-250-LT-LED	4%	98%	4%	99%	4%	99%

* Kanlux SA is not liable for the results of design changes introduced by the manufacturers of the above-mentioned dimmers that can affect the

KANLUX IQ-LEDDIM A60 8,5W

Dimmer	1 IQ-LEDDIM lamp		2 IQ-LEDDIM lamps		4 IQ-LEDDIM lamps	
Manufacturer – model	minimum level	maximum level [%]	minimum level [%]	maximum level [%]	minimum level	maximum level [%]

RS16/315 GLE 230V 300W	5%	100%	5%	100%	5%	100%
32ELEDM	7%	98%	7%	99%	6%	98%
067083A 16W05 31 CXM14(TGEU0001)	5%	91%	5%	91%	5%	91%
Dignet LED Smart Rotary dimmer/Switch XPERT-smaller dimmer	0%	99%	0%	99%	0%	99%
DGLCDM400(same than Dignet MEDM)	6%	98%	5%	99%	5%	99%
marisio Dimmer Resistivo 110V 20-150W(220V 40-300W)	3%	100%	4%	100%	5%	100%
KAOYI KDT-200A 220-240V 5-200W	10%	100%	6%	100%	5%	100%
P250 34373 TQP251W 216-253V 40-250W	5%	100%	6%	100%	6%	100%
C0143 250W	0%	99%	0%	100%	0%	100%
P400 87222 TQP401W 216-253V 60-400W	0%	100%	3%	100%	5%	100%
Wickes W195127W 230-240V 330W	0%	100%	0%	100%	0%	100%
MARBO HDR-400 200-240V 60-400W	0%	99%	0%	99%	0%	99%
Wickes W711324W 200-240V 60-400W	0%	98%	0%	100%	0%	100%
KOPP 230V 50HZ 40-400W arktis-weiB 809702013	0%	99%	0%	99%	0%	100%
GIRA 2262 230/240V 20-500W 50HZ	8%	98%	9%	99%	10%	99%
MEG5133-0000 230V 50HZ 40-600W/VA	0%	99%	0%	99%	1%	100%
Licht-Management 225NV DE AC 230/240V 20-500W 50HZ	7%	99%	8%	99%	8%	99%
ABB 2251 UCGL-92-507 230V 50Hz 400W	1%	99%	1%	100%	1%	100%
DANLERS 230V 60-400W	0%	99%	0%	100%	0%	100%
Dimmer Switch 2	3%	100%	4%	100%	5%	100%
ZGRID500	0%	100%	0%	100%	0%	100%
Elektronischer Dimmer 40-400VA 230V 10% 50HZ	0%	98%	0%	99%	0%	100%
L2501G2W PKA014 UK	0%	99%	0%	100%	0%	100%
Licht-Management 225NV	7%	99%	7%	100%	8%	100%
VIW 14153	0%	100%	0%	100%	0%	100%
Govena PRO-250-LT-LED	7%	99%	7%	99%	7%	99%

* Kanlux SA is not liable for the results of design changes introduced by the manufacturers of the above-mentioned dimmers that can affect the compatibility with Kanlux IQ-LEDDIM light sources